KB3 HiFi キーボードドライバーのインストール方法:

1. KB3HiFi キーボード専用 Windows ドライバーをダウンロードします。KB3 HiFi キーボード固有 のドライバーと Fiio ユニバーサル DAC ドライバーは異なるため、誤ってダウンロードしないよう ご注意ください。

2. 圧縮されたパッケージを解凍し、「FiiO USB Audio Drivers Setup」をダブルクリックしてイン ストールします。デフォルトでは、インストールが完了するまで「next」をクリックします。「Close」 をクリックして、インストール・インターフェースを終了します。

🔁 FiiO USB Audio Drivers			_		×
Installation Complete					
FiiO USB Audio Drivers has been succes	sfully installed.				
Click "Close" to exit.					
	Cancel	< <u>B</u> ack		<u>C</u> lose	

3. KB3 HiFi キーボード固有のドライバーと Fiio ユニバーサル DAC ドライバーは異なるため、KB3 を Windows コンピューターに接続すると、Fiio コントロールパネルに KB3HiFi ドライバーが表示 されません。

KB3 HiFi ドライバーは、音楽プレーヤーソフトウェアで確認できます。foobar を例にとると、KB3 HiFi ドライバー「ASIO:Fiio USB Audio Drivers」が File-Preferences-Output-Device にあり、ド ライバーのインストールが成功したことを示しています。

Preferences: Output				?	\times	
Components Components Components Components Colors and Fonts Colors and F	Pevice ASIO : Filo ASIO Driver Null Output ASIO : ASIO ADL v2 ASIO : Filo ASIO Driver ASIO : Filo ASIO Driver ASIO : Filo KA2 Usidio Device FASIO : Filo KA3 Usidio Device ASIO : Filo KA3 Usidio Device Default : Primary Sound Driver Default : Primary Sound Driver Default : Primary Sound Driver (Exclusive) Default : Realtek Digital Output (Realtek High Definition Audio) Default : Realtek Digital Output (Realtek High Definition Audio) [exclusive] Default : Fili (Filo KB3) Default : Eatiet Digital Output (Realtek High Definition Audio) [exclusive] WASAPE (Rared) : Default : Sound Driver [exclusive] WasAPE (Rared) : Default : Sound Pevice					
- Devices - AsIO - Shell Integration ✓ Tools - ReplayGain Scanner	Event Pause and stop Seek	5) Fade in 100 ms 100 ms	Fade out 100 ms 100 ms			
··· SACD ··· Tagging ··· freedb Tagger ··· Advanced	Manual track change	100 ms	100 ms			
	Reset all Reset page		OK Cano	cel Ar	oply	